

ТАБЛИЦА СЕЛЕКТИВНОСТИ AV-6, AV-10

Серия		AV-6, 10 кривая B (3-5 In) ГОСТ 50345													
AV-6, 10 кривая B (3-5 In) ГОСТ 50345	In, A	1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	
	1	5In			12	18	30	48	60	75	96	120	150	189	
	2	5In					30	48	60	75	96	120	150	189	
	3	5In					30	48	60	75	96	120	150	189	
	4	5In						48	60	75	96	120	150	189	
	6	5In							60	75	96	120	150	189	
	10	5In										120	150	189	
	16	5In												189	
	20	5In													
	25	5In													
	32	5In													
	40	5In													
	50	5In													
	63	5In													
AV-6, 10 кривая C (5-10)	In, A	1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	
	1	10In					30	48	60	75	96	120	150	189	
	2	10In						48	60	75	96	120	150	189	
	3	10In							60	75	96	120	150	189	
	4	10In									96	120	150	189	
	6	10In										120	150	189	
	10	10In													
	16	10In													
	20	10In													
	25	10In													
	32	10In													
	40	10In													
	50	10In													
	63	10In													
AV-6, 10 кривая D (10-20 In)	In, A	1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	3In	
	1	20In						48	60	75	96	120	150	189	
	2	20In									96	120	150	189	
	3	20In										120	150	189	
	4	20In												189	
	6	20In													
	10	20In													
	16	20In													
	20	20In													
	25	20In													
	32	20In													
	40	20In													
	50	20In													
	63	20In													

ТАБЛИЦА СЕЛЕКТИВНОСТИ AV-6, AV-10

Серия		AV-6, 10 кривая C (5-10 In) ГОСТ 50345													
AV-6, 10 кривая B (3-5 In) ГОСТ 50345	In, A	1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In
	1	5In		15	20	30	50	80	100	125	160	200	250	315	
	2	5In				30	50	80	100	125	160	200	250	315	
	3	5In					50	80	100	125	160	200	250	315	
	4	5In					50	80	100	125	160	200	250	315	
	6	5In						80	100	125	160	200	250	315	
	10	5In								125	160	200	250	315	
	16	5In										200	250	315	
	20	5In											250	315	
	25	5In												315	
	32	5In													
	40	5In													
	50	5In													
	63	5In													
AV-6, 10 кривая C (5-10 In)	In, A	1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In
	1	10In			20	30	50	80	100	125	160	200	250	315	
	2	10In					50	80	100	125	160	200	250	315	
	3	10In						80	100	125	160	200	250	315	
	4	10In						80	100	125	160	200	250	315	
	6	10In								125	160	200	250	315	
	10	10In										200	250	315	
	16	10In													
	20	10In													
	25	10In													
	32	10In													
	40	10In													
	50	10In													
	63	10In													
AV-6, 10 кривая D (10-20 In)	In, A	1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In
	1	20In					50	80	100	125	160	200	250	315	
	2	20In						80	100	125	160	200	250	315	
	3	20In								125	160	200	250	315	
	4	20In									160	200	250	315	
	6	20In											250	315	
	10	20In													
	16	20In													
	20	20In													
	25	20In													
	32	20In													
	40	20In													
	50	20In													
	63	20In													

ТАБЛИЦА СЕЛЕКТИВНОСТИ AV-6, AV-10

Серия		AV-6, 10 кривая С [5-10 In] ГОСТ 50345														
AV-6, 10 кривая В (3-5 In) ГОСТ 50345	In, A		1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток		10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In
	1	5In			30	40	60	100	160	200	250	320	400	500	630	
	2	5In					60	100	160	200	250	320	400	500	630	
	3	5In						100	160	200	250	320	400	500	630	
	4	5In						100	160	200	250	320	400	500	630	
	6	5In								200	250	320	400	500	630	
	10	5In									250	320	400	500	630	
	16	5In											400	500	630	
	20	5In												500	630	
	25	5In													630	
	32	5In														
	40	5In														
	50	5In														
	63	5In														
AV-6, 10 кривая С (5-10)	In, A		1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток		10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In
	1	10In			30	40	60	100	160	200	250	320	400	500	630	
	2	10In					60	100	160	200	250	320	400	500	630	
	3	10In						100	160	200	250	320	400	500	630	
	4	10In						100	160	200	250	320	400	500	630	
	6	10In							160	200	250	320	400	500	630	
	10	10In									250	320	400	500	630	
	16	10In											400	500	630	
	20	10In												500	630	
	25	10In													630	
	32	10In														
	40	10In														
	50	10In														
	63	10In														
AV-6, 10 кривая D (10-20 In)	In, A		1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток		10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In	10In
	1	20In				40	60	100	160	200	250	320	400	500	630	
	2	20In						100	160	200	250	320	400	500	630	
	3	20In							160	200	250	320	400	500	630	
	4	20In							160	200	250	320	400	500	630	
	6	20In									250	320	400	500	630	
	10	20In											400	500	630	
	16	20In														
	20	20In														
	25	20In														
	32	20In														
	40	20In														
	50	20In														
	63	20In														

ТАБЛИЦА СЕЛЕКТИВНОСТИ AV-6, AV-10, DVA-6

Серия		AV-6, 10 кривая C (5-10 In) ГОСТ 50345														
DVA-6 кривая B (3-5 In) ГОСТ 51327	In, A		1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток		5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In
	1	5In			15	20	30	50	80	100	125	160	200	250	315	
	2	5In					30	50	80	100	125	160	200	250	315	
	3	5In						50	80	100	125	160	200	250	315	
	4	5In						50	80	100	125	160	200	250	315	
	6	5In							80	100	125	160	200	250	315	
	10	5In									125	160	200	250	315	
	13	5In												200	250	315
	16	5In												200	250	315
	20	5In													250	315
	25	5In														315
	32	5In														
	40	5In														
	50	5In														
63	5In															
DVA-6 кривая C (5-10)	In, A		1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток		5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In
	1	10In				20	30	50	80	100	125	160	200	250	315	
	2	10In						50	80	100	125	160	200	250	315	
	3	10In							80	100	125	160	200	250	315	
	4	10In							80	100	125	160	200	250	315	
	6	10In									125	160	200	250	315	
	10	10In											200	250	315	
	13	10In													315	
	16	10In														
	20	10In														
	25	10In														
	32	10In														
	40	10In														
	50	10In														
63	10In															
DVA-6 кривая D (10-20 In)	In, A		1	2	3	4	6	10	16	20	25	32	40	50	63	
	Ток		5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In	5In
	1	20In						50	80	100	125	160	200	250	315	
	2	20In							80	100	125	160	200	250	315	
	3	20In									125	160	200	250	315	
	4	20In										160	200	250	315	
	6	20In												250	315	
	10	20In														
	13	20In														
	16	20In														
	20	20In														
	25	20In														
	32	20In														
	40	20In														
	50	20In														
63	20In															

ТАБЛИЦА СЕЛЕКТИВНОСТИ AV POWER - AV-6, AV-10

		AV POWER-1												AV POWER-2												AV POWER-3												AV POWER-4																																									
		Расцепитель ТМ (10I _n ±20%)																																																																													
	In, A	AV-6, 10 кривая В (3-5 In) ГОСТ 50345												AV-6, 10 кривая С (5-10)												AV-6, 10 кривая С (5-10)												AV-6, 10 кривая С (5-10)																																									
		5 In						10 In						20 In						10 In						20 In						10 In						20 In																																									
		63	50	40	32	25	20	16	10	6	4	3	2	1	63	50	40	32	25	20	16	10	6	4	3	2	1	63	50	40	32	25	20	16	10	6	4	3	2	1	63	50	40	32	25	20	16	10	6	4	3	2	1	63	50	40	32	25	20	16	10	6	4	3	2	1	63	50	40	32	25	20	16	10	6	4	3	2	1
	Ток, А																																																																														

ТАБЛИЦА СЕЛЕКТИВНОСТИ AV POWER

	Выше- стоящий аппарат	AV POWER-1														AV POWER-2							AV POWER-3						AV POWER-4			
		Расцепитель ТМ																														
AV POWER-1	In, A	10	16	20	25	32	40	50	63	80	100	125	140	160	100	125	140	160	180	200	225	250	250	315	350	400	500	630	630	700	800	
	Ток, kA	35																														
	10		128	160	200	256	320	400	504	640	800	1000	1120	1280	800	1000	1120	1280	1440	1600	1800	2000	2000	2520	2800	3200	4kA	5kA	5kA	5,6kA	6,4kA	
	16																															
	20																															
	25																															
	32																															
	40																															
	50	35																														
	63																															
	80																															
	100																															
	125																															
	140																															
	160																															
	AV POWER-2	In, A	10	16	20	25	32	40	50	63	80	100	125	140	160	100	125	140	160	180	200	225	250	250	315	350	400	500	630	630	700	800
		Ток, kA	35																													
100															1280				1280	1440	1600	1800	2000	2000	2520	2800	3200	4kA	5kA	5kA	5,6kA	6,4kA
125																																
140																																
160																																
180																																
200																																
225																																
250																																
315																																
350																																
400																																
500																																
630																																
AV POWER-3		In, A	10	16	20	25	32	40	50	63	80	100	125	140	160	100	125	140	160	180	200	225	250	250	315	350	400	500	630	630	700	800
		Ток, kA	35																													
	250																															
	315																															
	350																															
	400																															
	500																															
AV POWER-4	In, A	10	16	20	25	32	40	50	63	80	100	125	140	160	100	125	140	160	180	200	225	250	250	315	350	400	500	630	630	700	800	
	Ток, kA	35																														
	630																															
	700																															
800																																

ТАБЛИЦА СЕЛЕКТИВНОСТИ ЕТУ

		Вышестоящий аппарат	AV POWER-1				AV POWER-2	AV POWER-3		AV POWER-1	
			Расцепитель ЕТУ								
Нижестоящий аппарат	AV POWER-1	In, A	32	63	100	160	250	400	630	1000	
		Ток, кА	50								
		10									
		16									
		20		1,7							
		25			1,7						
		32									
		40					2,4				
		50	50					3,5	6,4	10	10
		63									
		80									
		100									
		125									
		140									
		160									
		Нижестоящий аппарат	AV POWER-2	In, A	32	63	100	160	250	400	630
Ток, кА	50										
100											
125								3,5			
140									6,4	10	
160	50										10
180								2,4			
200											
225											
250									3	6,4	
Нижестоящий аппарат	AV POWER-3	In, A	32	63	100	160	250	400	630	1000	
		Ток, кА	50								
		250							3		
		315								6,4	10
		350								4,2	
		400	50								6,4
		500									
630											
Нижестоящий аппарат	AV POWER-4	In, A	32	63	100	160	250	400	630	1000	
		Ток, кА	50								
		630									7,5
		700	50								
800											